

7.5 Functions in 5-channel DMX mode

Channel	LED	Value	Function
1	Ambient LED	0...255	Red intensity (0 % to 100 %)
2	Ambient LED	0...255	Green intensity (0 % to 100 %)
3	Ambient LED	0...255	Blue intensity (0 % to 100 %)
4	Ambient LED	0...255	White intensity (0 % to 100 %)
5	Strobe LED	0...3	open
		4...103	Strobe effect, increasing speed
		104...107	open
		108...207	Pulsing strobe effect, increasing speed
		208...212	open
		213...251	Random strobe effect, increasing speed
		252...255	open

7.6 Functions in 8-channel DMX mode

Channel	LED	Value	Function
1	Ambient LED	0...255	Dimmer (0 % to 100 %)
2	Strobe LED	0...3	open
		4...103	Strobe effect, increasing speed
		104...107	open
		108...207	Pulsing strobe effect, increasing speed
		208...212	open
		213...251	Random strobe effect, increasing speed
		252...255	open
3	Ambient LED	0...255	Red intensity (0 % to 100 %)
4	Ambient LED	0...255	Green intensity (0 % to 100 %)
5	Ambient LED	0...255	Blue intensity (0 % to 100 %)
6	Ambient LED	0...255	White intensity (0 % to 100 %)
7	Ambient LED	0...99	open

Channel	LED	Value	Function
		100...255	Automatic mode
8	Ambient LED	0...255	Run speed automatic mode, increasing speed

7.7 Functions in 21-channel DMX mode

Channel	LED	Value	Function
1	Ambient LED	0...255	Dimmer (0 % to 100 %)
2	Ambient LED	0...255	White intensity (0 % to 100 %)
3	Strobe LED	0...3	open
		4...103	Strobe effect, increasing speed
		104...107	open
		108...207	Pulsing strobe effect, increasing speed
		208...212	open
		213...251	Random strobe effect, increasing speed
		252...255	open
4	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 1
5	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 1
6	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 1
7	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 2
8	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 2

Channel	LED	Value	Function
9	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 2
10	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 3
11	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 3
12	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 3
12	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 4
14	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 4
15	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 4
16	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 5
17	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 5
18	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 5
19	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 6
20	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 6
21	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 6

7.8 Functions in 23-channel DMX mode

Channel	LED	Value	Function
1	Ambient LED	0...255	Dimmer (0 % to 100 %)
2	Ambient LED	0...255	White intensity (0 % to 100 %), segment 1
3	Ambient LED	0...255	White intensity (0 % to 100 %), segment 2
4	Ambient LED	0...255	White intensity (0 % to 100 %), segment 3
5	Strobe LED	0...3	open
		4...103	Strobe effect, increasing speed
		104...107	open
		108...207	Pulsing strobe effect, increasing speed
		208...212	open
		213...251	Random strobe effect, increasing speed
		252...255	open
6	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 1
7	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 1
8	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 1

Channel	LED	Value	Function
9	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 2
10	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 2
11	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 2
12	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 3
13	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 3
14	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 3
15	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 4
16	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 4
17	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 4
18	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 5
19	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 5
20	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 5
21	Ambient LED	0...255	Red intensity (0 % to 100 %), segment 6
22	Ambient LED	0...255	Green intensity (0 % to 100 %), segment 6
23	Ambient LED	0...255	Blue intensity (0 % to 100 %), segment 6